

---

## FC503 Addressable Fire Control Panels

The FC503 easy-to-programme control panel has a 4-line, 40 character per line, LCD module display with a backlight, which provides written information regarding the system status, such as temperature, CO level, and smoke level, and is also used for programming the control panel. The front panel controls enable text and configuration changes.

The FC503 auto-addressing panel has 3 in 1 loops that can support up to 250 addressable devices and 32 zones. An IP board is available as an option for this panel.

**Figure 1: FC503 front panel with FC500 repeater**



### Specifications

- The mechanical enclosure is made of sheet metal.
- The front door is plastic.
- H x W x D: 493mm x 429mm x 124mm

# Features

## Additional Panel Features

- Up to 800mA current dynamically shared across 3 circuits in 1 loop
- Auto mapping with Intelli-Zone feature
- Online Help function
- USB interface dual role Host/Device
- Multi users and multi installers (Up to 2 installers, 8 users)
- Walk test function
- 4000 Event Log
- Loop break location
- On board PSTN communicator
- GSM/GPRS as external module
- Up to 8 repeaters and up to 7 FC500 series panel clients
- Event transmission through PSTN and IP
- Automatic drift compensation

## Software Features

- Fast and simple system configuration, also offline
- Transferable user database
- Device graphic displayed
- Battery and wiring calculation
- Customizable cables database
- Visualization of all the devices assigned to a single zone
- Remote real time visualization of control panel loop and zone status, and so on.
- Easy Remote user interface with control buttons (reset, silence, evacuate)
- Multilevel map based on a tree structure
- Access device data from any pages of the map
- Configuration downloadable to USB memory stick
- Capability to print zone label sheet for front panel customization

# Ordering information

**Table 1: Product and accessories ordering information**

Order number	Product details
<b>Variants</b>	
557.200.725	<b>FC503:</b> 3 Loop Panel 250 Points
<b>Accessories: SKU Description</b>	
508.031.742	<b>FC500MFI:</b> Multifunctional Interface

**Table 1: Product and accessories ordering information**

Order number	Product details
508.031.743	<b>FC500IP3:</b> IP Module
508.032.036	<b>FC500BX:</b> Cabinet for Spare 38Ah Batteries
508.032.037	<b>USB 5m:</b> USB 5m Cable Type A
508.032.042	<b>FC500DISP:</b> Spare Display
557.202.726	<b>FC-MAE:</b> FC500 Panels Monitoring Software
557.200.727	<b>FC500</b> FireClass Repeater
508.032.044	Spare Motherboard for FC-503 3 Loop FireClass Panel


## Performance characteristics

**Table 2: Performance characteristics**

Description	FC503	FC500
Dimensions H x W x D mm	493 x 429 x 124	234 x 345 x x55.7
Weight	8 kg	2.7kg
Operating Temp	-5°C ÷ 40°C	
Storage Temp	-40 ÷ 80 °C	
Humidity	Up to 95% Non Condensing	
Supply Voltage	230VAC 50Hz - 15/ +10%	19 Vdc - 30 Vdc
PSU I <sub>max</sub> (Input Current)	1,5A	130 mA (dc)
Aux output rated voltage	27,6 Vdc	NA
Max Battery Size	17 Ah	NA
Loop power	800mA	NA
IP Rating	IP30	
Enclosure colour (cabinet and door)	RAL 7035	

## Approvals

**Table 3: Approvals**

	 0051 19 Tyco Fire & Security GmbH, Victor von Bruns-Strasse 21, 8212 Neuhausen am Rheinfall, Switzerland.	CPR Approval			European Type Approvals						International Listings		
		EN 54-2	EN 54-4	EN 54-21	MED	LPCB	VDS	AFNOR	FNO	SB SC	FP ANZ	HK FSD	TFTF
FC503	DOP-2018-4260	x	x	x									

All required Declarations and certificates are publically available on the website [www.fireclass.net](http://www.fireclass.net) and are searchable by number or model name. The above fire detection products are components designed for use in Addressable Systems exclusively available to registered partners only. They

are intended for installation by trained registered personnel only. Systems should be installed and configured according to local regulations.

## Comparison of FC501, FC503, and FC506 features

**Table 4: Comparison of FC501, FC503, and FC506 features**

Feature	FC501	FC503	FC506
<b>Addressable loops</b>			
No. of Loops	1 Loop	1 Loop	2 Loops
Loop Splitter / Sub-Loops	3	3	6
Max Current Draw per Loop	0.5A	1A	1A
No. of Devices	128	250	500
<b>Outputs</b>			
Fault	1	1	1
Fire	1	1	1
Programmable Open collector Outputs	2	2	2
USB Interface	1	1	1
RS232 Interface	1	1	1
RS485 Interface	1	1	1
24V (for RS485 Devices)	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
24 V Auxiliary	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
24V Resettable	1 , Max Current: 0.5 A	1 , Max Current: 1 A	1 , Max Current: 1 A
Sounder / NAC Outputs	2 , Max Current: 0.5 A per NAC	2 , Max Current: 0.5 A per NAC	2 , Max Current: 0.5 A per NAC
<b>Power supply</b>			
AC Mains Voltage	230Vac -15%/+10%, 50-60Hz		
PSUs	BAW75T24 (27.6V, 2.7A)	BAQ140T24 (27.6V, 5.5 A)	BAQ140T24 (27.6V, 5.5 A)
Maximum Battery Size (Inside Panel)	2 (12A/h)	2 (17A/h)	2 (17A/h)
Maximum Battery Capacity	38 Ah	38 Ah	38 Ah
Battery Optional Box	YES	YES	YES
Panel Cabinet	Plastic Box	Metal Box, Plastic Door	Metal Box, Plastic Door
<b>Management software</b>			
Software	FireClass console	FireClass console	FireClass console

**Table 4: Comparison of FC501, FC503, and FC506 features**

<b>Feature</b>	<b>FC501</b>	<b>FC503</b>	<b>FC506</b>
Communication Channels	RS232, USB, RS485,IP	RS232, USB, RS485,IP	RS232, USB, RS485,IP
SW Zones	32	32	32
Number of zonal LEDs	8	8	8
Auto Addressing	YES	YES	YES
Events logged	4000	4000	4000
FC500 MFI Interface	4	4	4
FC500 Repeaters	4	8	8
FC500 Clients	No Support	7	7
<b>Standard compliance</b>			
EN54-2	x	x	x
EN54-4	x	x	x
EN54-21	x	x	x
<b>Communicators</b>			
PSTN (Voice, Data)	On Board	On Board	On Board
IP	FC500IP (Add On)	FC500IP (Add On)	FC500IP (Add On)

